


QX61 BSP RS-485 Adapter



Document Details

Version

v1.0 [EDIT]

(v1.0 published [EDIT])

Firmware

Firmware version can be verified on Verkada

Command command.verkada.com.

Product Models

This install guide pertains to models QX61

© Copyright 2025 Verkada Inc. All rights reserved.

Verkada and the Verkada logo are registered trademarks or service marks of Verkada Inc. ("Verkada"). All other trademarks are the property of their respective owners.


Verkada may make changes to this document at any time without notice. The information presented herein may be inaccurate or outdated, and Verkada is under no obligation to maintain it. ALL INFORMATION IS PROVIDED "AS-IS" AND WITHOUT ANY WARRANTIES, IMPLIED, EXPRESS, OR OTHERWISE. VERKADA DISCLAIMS LIABILITY FOR ALL DAMAGES, INCLUDING WITHOUT LIMITATION ANY DIRECT, INDIRECT, SPECIAL, INCIDENTAL, PUNITIVE, OR CONSEQUENTIAL DAMAGES, ARISING OUT OF USE OF THIS DOCUMENT.

Any intellectual property rights relating to Verkada products are and shall remain Verkada's exclusive property. Use of any Verkada product is subject to Verkada's end user agreement or other executed agreement with Verkada. No license, either expressed or implied, to use or distribute any Verkada product is granted under this document.


This document may not be sold, resold, licensed or sublicensed and may not be transferred without Verkada's prior written consent. No part of this document may be reproduced in whole or in part without the express written consent of Verkada.




What's in the Box




**BSP RS-485
Adapter**




Mount Plate



**Wood Screws
M3.5 x 20mm
(2 pcs)**



**Wall Anchors
(2 pcs)**



**T10 Security
Torx L-Key**

What you'll need

- A smartphone or laptop
- #2 Phillips head and power drill (if using mount plate)
- 1/4 inch (6.5mm) drill bit for wall anchor pilot holes (if using mount plate)
- 1/8 inch (3mm) drill bit for wood screw pilot holes (if using mount plate)

Connect


For easy registration and setup, scan the QR code on the product.

If you prefer to manually register your product, please proceed to:


verkada.com/start

Overview

Front



Back



Status LED Behaviors

- **Solid Blue**
Online and connected
- ⚙ **Flashing Blue**
Not online and not connected
- ⚙ **Flashing Orange**
Updating firmware

Technical Specifications

Power Input	13.68W maximum input
Input Voltage	12-36 VDC Input
IOs	2x RS485 Ports (Independent) 1x BSP OUT
Dimensions	47.4 x 79.8 x 30.9 mm (1.87 x 3.14 x 1.22 in)
Weight	87g (3.1oz)
Tamper Detection	Yes
Operating Temperature	-10 °C-50°C, 0-90% relative humidity
Compliance	FCC Part 15B Class B, ICES-003 Class B, CE, UKCA, VCCI, RCM, IK07, Indoor Use Only, to be used in controlled, protected, and/or restricted access areas.
Mounting Options	Wall or junction box
Included Accessories	T10 security Torx hex key, mounting hardware kit

Placement Options

The Adapter can be mounted on a wall with the Mount Plate, or placed inside a junction box.



Mounting on wall



Placing inside a junction box

Installation

Mounting

Mounting to Wall

Cable routing options: The cable can be passed through the wall or the cable exit.

Loosen the set screw and take off the Mount Plate from the device.




Use the Mount Plate as a template to mark holes for mounting and cable pass-through, if needed.

Secure the Mount Plate using the screws and wall anchors.

Refer to the *Wiring Instruction* section of this document.

After completing the wiring, engage the hook and swing the device toward the mount plate.

Tighten the security screw to lock the Adapter in place.



Mounting

Placing inside a junction box

Pass the wire through the junction box conduit hole.


Refer to the *Wiring Instruction* section of this document.



Terminal Block Configuration


4-wire RS485 In

Connects QX61 to RS485 on panel.




4-wire RS485 Out

RS485 pass through connection for another RS485 device to connect to panel.




2-wire BSP Out

Connects to BSP devices like the QX51.



BSP RS-485 Adapter

The QX61 is an RS485 adapter for Verkada's BSP addressable sensor wiring. It enables support addressable alarm sensors on a compatible Verkada Alarm panel. Each QX61 supports one BSP addressable cable run, or one RS485 passthrough.



- 1 Connect the QX61 to the RS-485 port on any Verkada Alarm Panel using a 4-conductor cable. Connect the QX51 either to a QX61 or directly to the BSP port on a BP42.
- 2 Daisy-chain the BSP cable from the QX61 through each QX51 module.
- 3 Connect your first sensor to Zone 1.
- 4 Connect your second sensor to Zone 2.
If using a powered sensor (like a motion detector), use the 12V AUX terminal for power.

Note: Each QX51 is limited to a maximum of one powered sensor. A maximum of 50 powered sensors are supported on one BSP run.

Wiring Best Practices

Ensure each cable is stripped sufficiently to allow the copper conductor to make full contact within the terminal block. Tighten all terminal screws and verify that no wires are loose.

Appendix

Compliance

FCC Compliance	This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. NOTE: This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.
ISED Compliance	This device complies with ISED's licence-exempt RSSs. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Le présent appareil est conforme aux CNR d'ISED applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes : (1) le dispositif ne doit pas produire de brouillage préjudiciable, et (2) ce dispositif doit accepter tout brouillage reçu, y compris un brouillage susceptible de provoquer un fonctionnement indésirable.

Appendix

Support

Thank you for purchasing this Verkada product. If for any reason you're experiencing issues or need assistance, please contact our 24/7 Technical Support Team immediately.

Sincerely,
The Verkada Team
verkada.com/support

